

Porovnávací tabulka diod

Náhrady univerzálních diod pro malé signály	
Tesla	Náhrada
KA206	1N4148
KA261	1N4148
KA262	1N4148
KA263	1N4148
KA264	1N4148
KA265	1N4148
KA266	1N4148
KA267	1N4148

Zenerovy diody	
Tesla	Náhrada
KZ140	BZX83V003.0
KZ141	BZX83V005.1
KZ260/xx	BZX85Vxx, BZYxx

Usměrňovací diody do 1A	
Tesla	Náhrada
KY130	1N4007
KY132	1N4007
KY701	1N5408
KY702	1N5408
KY703	1N5408
KY704	1N5408
KY705	1N5408
KY706	1N5408
KY721	1N5408
KY722	1N5408
KY723	1N5408
KY724	1N5408
KY725	1N5408
KY726	1N5408

